



**Manufacturer:**  
Amphenol Fiber Optic Products

**Product Name:**  
Amphenol 906 SMA Connector, 128 $\mu$ m (micron) Stainless Steel Ferrule, 3mm Boot

**Manufacturer Part Number:**  
906-122-5004



▶ [Click here for more details on the Amphenol 906 SMA Connector, 128 \$\mu\$ m \(micron\) Stainless Steel Ferrule, 3mm Boot](#)

# SMA Stainless Steel Ferrule Connectors

- ▶ The Stepped Ferrule Series is designed to center the fiber for precise alignment.
- ▶ Features a stepped ferrule and durable stainless steel hex nut for secure connections.
- ▶ Provides high reliability and performance in demanding fiber optic applications.



**Contact the professionals at Fiber Optic Center for a quote or to get more details.**

23 Centre Street • New Bedford, MA 02740 USA • [focenter.com](http://focenter.com) • 508-992-6464 • (800) 473-4237 • [sales@focenter.com](mailto:sales@focenter.com)

*Product specifications and data are subject to change without notice.*



**Manufacturer:**  
Amphenol Fiber Optic Products

**Product Name:**  
Amphenol 906 SMA Connector, 128µm (micron) Stainless Steel Ferrule, 3mm Boot

**Manufacturer Part Number:**  
906-122-5004



▶ [Click here for more details on the Amphenol 906 SMA Connector, 128µm \(micron\) Stainless Steel Ferrule, 3mm Boot](#)


## SMA Stainless Steel Ferrule Connectors

Part Number	Front Ferrule Hole Size	Ferrule Length	Ferrule OD	Crimp Ferrule	Step Crimp Modified Ferrule	Coupling Nut Material	Coupling Nut Type	Centering Sleeve	O-Ring
906-122-5000 (very common)	144µm (+5/-0 µm)	9.86 mm (0.3882")	3.08 mm (.120")	Yes	Yes	Stainless Steel 303	Hex	Yes	Yes
906-122-5004 (very common)	128µm (+5/ 0 µm)	9.86 mm (0.3882")	3.08 mm (.120")	Yes	Yes	Stainless Steel 303	Hex	Yes	Yes
906-122-5014	231µm (+10/-0 µm)	9.86 mm (0.3882")	3.08 mm (.120")	Yes	Yes	Stainless Steel 303	Hex	Yes	Yes
906-122-5015	245µm (+10/-0µm)	9.86 mm (0.3882")	3.08 mm (.120")	Yes	Yes	Stainless Steel 303	Hex	Yes	Yes
906-122-5031	1000µm (+15/-0 µm)	9.86 mm (0.3882")	3.08 mm (.120")	Yes	Yes	Stainless Steel 303	Hex	Yes	Yes

**Contact the professionals at Fiber Optic Center for a quote or to get more details.**

23 Centre Street • New Bedford, MA 02740 USA • [focenter.com](http://focenter.com) • 508-992-6464 • (800) 473-4237 • [sales@focenter.com](mailto:sales@focenter.com)

*Product specifications and data are subject to change without notice.*



**Manufacturer:**  
Amphenol Fiber Optic Products

**Product Name:**  
Amphenol 906 SMA Connector, 128µm (micron) Stainless Steel Ferrule, 3mm Boot

**Manufacturer Part Number:**  
906-122-5004



▶ [Click here for more details on the Amphenol 906 SMA Connector, 128µm \(micron\) Stainless Steel Ferrule, 3mm Boot](#)

## SMA Stainless Steel Ferrule Connectors

Part Number	Boot Diameter- Rear ID	Boot Logo	Boot Color	Cap Type	Cap Color	Tether Loop	Cap Slit	Cap Logo
906-122-5000 (very common)	2.8 mm	Yes	Black	T-Style	Black	No	No	No
906-122-5004 (very common)	2.8 mm	Yes	Black	T-Style	Black	No	No	No
906-122-5014	2.8 mm	Yes	Black	T-Style	Black	No	No	No
906-122-5015	2.8 mm	Yes	Black	T-Style	Black	No	No	No
906-122-5031	2.8 mm	Yes	Black	T-Style	Black	No	No	No

**Meets QA Standards:**

REACH 240 Compliant  
RoHS Certificate of Compliance



**Contact the professionals at Fiber Optic Center for a quote or to get more details.**

23 Centre Street • New Bedford, MA 02740 USA • [focenter.com](http://focenter.com) • 508-992-6464 • (800) 473-4237 • [sales@focenter.com](mailto:sales@focenter.com)

*Product specifications and data are subject to change without notice.*